- 1. Connect to the modem via Wire or Wireless
- 2. Open a browser (Chrome, Firefox, Safari, etc.) and enter <u>192.168.1.1</u> in the address bar
- 3. Enter admin as the username and @HuaweiHgw as the password
- 4. On the left-hand side click Advanced Configuration



5. On the left-hand side click WAN Configuration and then click New

₩2 DG8245V-10 Fast Setting   admin Lo									
	WAN Configuration		WAN Configuration						
命	LAN Configuration	~	On this page, you can configure WAN port parameters. A home gateway communicates with an upper-layer device through the WAN port. During the communication, WAN port parameters must be consistent with upper-layer device						
+	Security Configura	~	New     Delete       Connection Name     VLAN/Priority   Protocol Type						
Ø	Route	~							
<b>\$</b>	Forward Rules	~		1_TR069_VOIP_INTERNET	_R_GE_VID_10	10/0	IPv4/IPv6		
	Application V	~		2_TR069_VOIP_INTERNET_R_A	.DSL_0/110_VID_10	10/0	IPv4/IPv6		
				3_TR069_VOIP_INTERNET_F	R_VDSL_VID_10	10/0	IPv4/IPv6		
	WLAN	~							
	Voice	~							
	System Management	~							
	Maintenance Diagno.	~							

## 6. Make sure the settings match below and click Save

Basic Information						
Enable WAN:						
Access Type:	PTM upstream					
Encapsulation Mode:	○ IPoE					
Protocol Type:	IPv4 v					
WAN Mode:	Route WAN V					
Service Type:	INTERNET V					
Enable VLAN:						
VLAN ID:	10 *(1-4094)					
802.1p Policy:	Use the specified valı 🗸					
802.1p:	0 ~					
MRU:	1500 (1-1540)					
User Name:	er@contactenergy.co.nz					
Password:	••••••					
Enable LCP Detection:						
Binding Options:	LAN1 LAN2 LAN3 LAN4 SSID1 SSID2 SSID3 SSID4 SSID5 SSID6 SSID7 SSID8					
IPv4 Information						
IP Acquisition Mode:	○ Static ○ DHCP					
Enable NAT:						
NAT type:	Full cone NAT v					
Dialing Method:	Automatic V					
	Apply Cancel					