

1. Connect to the modem via Wire or Wireless
2. Open a browser (Chrome, Fire, Safari, etc.) and enter **192.168.1.1** in the address bar
  - Try **192.168.0.1** if this doesn't work
3. If you are prompt for a Username or Password, enter **admin** for this
4. Click the **Advanced** tab up the top
5. Navigate to **Network > Internet** and set the **Internet Connection Type** to **Dynamic IP** and click **Save**

The screenshot shows the TP-Link Advanced Network settings page. The 'Advanced' tab is selected at the top. In the left sidebar, 'Network' is highlighted, and 'Internet' is selected. The main content area is titled 'IPv4' and shows the following settings:

- Internet Connection Type: Dynamic IP
- IP Address: 192.168.0.1
- Subnet Mask: 255.255.255.0
- Default Gateway: 192.168.0.1
- Primary DNS: 1.1.1.1
- Secondary DNS: 2.2.2.2

Buttons for 'Renew' and 'Release' are visible. At the bottom right, a 'Save' button is highlighted.

6. Navigate to **Network > IPTV**, match the following settings and click **Save**

The screenshot shows the TP-Link Advanced Network settings page with the 'Advanced' tab selected. In the left sidebar, 'Network' is highlighted, and 'IPTV' is selected. The main content area is titled 'Settings' and shows the following IPTV settings:

- IGMP Proxy:  Enable
- IGMP Version: V2
- IPTV:  Enable IPTV
- Mode: Custom
- Internet VLAN ID: 10 | Internet VLAN Priority: 0 |  802.1Q Tag
- IP-Phone VLAN ID: 20 | IP-Phone VLAN Priority: 1
- IPTV VLAN ID: 30 | IPTV VLAN Priority: 2
- IPTV Multicast VLAN ID: | IPTV Multicast VLAN Priority: 0 |  Enable
- LAN1: Internet
- LAN2: Internet
- LAN3: Internet
- LAN4: Internet

A 'Save' button is highlighted at the bottom right.